


HF-855 System For 1 to 10 Apartments Installation Guide

Power: PH-P7

Note: Don't connect blue wire #6 if without Sub_monitor



Remarks:

1. One PH-P6 for 6 Apartments; and one PH-P7 for 3 pcs HF-855Ma
2. Please independently install one PH-P7 as a power supply if the resident needs to install 2 Monitors in his own apartment.
3. The wire specifications : AWG #20 at least
4. HF-855Ma programming: Press the button (S1) on the rear side, until you hear a beep. You have 30 seconds to press the key on 855C5 or 855K2. The HF-855Ma will be powered on and there is "Ding-Dong, Ding-Dong" sound twice to confirm the setting is successfully made.

NO:
HF-855-P6-02

DATE:
12 Apr. 2005